

DESIGN PAR 575 MSR

DMX channel's functions and values (6 DMX channels):

Channel 1 - PAN movement 8bit :

Channel 2 – Pan fine

Channel 3 - TILT movement 8bit :

Channel 4 – Tilt fine

Channel 5 - Speed pan/tilt movement

0-225	max to min speed
226-255	No function

Channel 6 – Lamp on/off, reset, internal programmes

0-19	normal control
20-39	no function
40-59	Lamp on
60-79	Lamp off
80-84	All motor reset
85-87	Scan motor reset
88-99	No function
100-119	Internal program 1
120-139	Internal program 2
140-159	Internal program 3
160-179	Internal program 4
180-199	Internal program 5
200-219	Internal program 6
220-239	Internal program 7
240-255	Auto program trigger by sound

