

DMX TRAITS

Eliminator Mini Par Bar - DMX Traits

Software Version *1.0*

CHANNEL	DMX VALUE	DESCRIPTION
1		Mode
	000 - 010	No function
	011 - 050	Macro A1: Macro color
	051 - 100	Macro A2: 18 color change
	101 - 150	Macro A3: Fade mode
	151 - 200	Macro A4: Sound active mode
	201 - 255	Macro A5: Strobe mode
2 (CH1 = 011 - 050)		Color Macro
	000 - 039	RGBW, all on
	040 - 049	Red
	050 - 059	Green
	060 - 069	Blue
	070 - 079	Yellow (RG)
	080 - 089	Cyan (GB)
	090 - 099	Purple (RB)
	100 - 109	White
	110 - 119	Orange (RG)
	120 - 129	Pink (RB)
	130 - 139	RW
	140 - 149	GB
	150 - 159	GW
	160 - 169	BW
	170 - 179	RGW
	180 - 189	RBW
	190 - 199	GBW
	200 - 209	RGB
	210 - 255	RGBW (all on)

CONTINUED ON NEXT PAGE

DMX TRAITS

Eliminator Mini Par Bar - DMX Traits

Software Version *1.0*

CHANNEL	DMX VALUE	DESCRIPTION
2 (CH1 = 101 - 150)		<i>Fade</i>
	000 - 039	All color fade
	040 - 049	Red color fade
	050 - 059	Green color fade
	060 - 069	Blue color fade
	070 - 079	Yellow color fade
	080 - 089	Cyan color fade
	090 - 099	Purple color fade
	100 - 109	White color fade
	110 - 119	Red + green
	120 - 129	Red + blue
	130 - 139	Red + white
	140 - 149	Green + blue
	150 - 159	Green + white
	160 - 169	Blue + white
	170 - 179	Red + green + white
	180 - 189	Red + blue + white
	190 - 199	Green + blue + white
	200 - 209	Red + green + blue
	210 - 255	Red + green + blue + white
2 (CH1 = 151 - 200)		<i>Sound Active</i>
	000 - 039	All color change
	040 - 049	All on
	050 - 059	Red color strobe
	060 - 069	Green color strobe
	070 - 079	Blue color strobe
	080 - 089	Yellow color strobe
	090 - 099	Cyan color strobe
	100 - 109	Purple color strobe
	110 - 119	White color strobe
	120 - 129	Orange color strobe
CONTINUED ON NEXT PAGE		

DMX TRAITS

Eliminator Mini Par Bar - DMX Traits

Software Version *1.0*

CHANNEL	DMX VALUE	DESCRIPTION
2 (CH1 = 151 - 200) (continued)		<i>Sound Active (continued)</i>
	130 - 139	Pink color strobe
	140 - 149	Red + white color strobe
	150 - 159	Dark green color strobe
	160 - 169	Green + white
	170 - 179	Blue + white
	180 - 189	Red + green + white
	190 - 199	Red + blue + white
	200 - 209	Green + blue + white
	210 - 255	Red + green + blue
2 (CH1 = 201 - 255)		<i>Strobe Mode</i>
	000 - 039	Color change
	040 - 049	GBW on + R strobe
	050 - 059	RBW on + G strobe
	060 - 069	RGW on + B strobe
	070 - 079	BW on + RG strobe
	080 - 089	RW on + GB strobe
	090 - 099	GW on + RB strobe
	100 - 109	RGB on + W strobe
	110 - 119	BW on + RG strobe
	120 - 129	GW on + RB strobe
	130 - 139	GB on + RW strobe
	140 - 149	RW on + GB strobe
	150 - 159	RB on + GW strobe
	160 - 169	RG on + BW strobe
	170 - 179	B on + RGW strobe
	180 - 189	G on + RBW strobe
	190 - 199	R on + GBW strobe
	200 - 209	W on + RGB strobe
	210 - 255	RGBW strobe
CONTINUED ON NEXT PAGE		

DMX TRAITS

Eliminator Mini Par Bar - DMX Traits

Software Version *1.0*

CHANNEL	DMX VALUE	DESCRIPTION
3	000 - 255	<i>Adjustable Speed</i> , slow to fast
4	000 - 255	<i>Master Dimming</i> , 0% - 100%
5	000 - 255	<i>Red color</i> , 0% - 100%
6	000 - 255	<i>Green color</i> , 0% - 100%
7	000 - 255	<i>Blue color</i> , 0% - 100%
8	000 - 255	<i>White color</i> , 0% - 100%